

**CREATURE I
LED CLOCK RADIO
MODEL EX-21
PRELIMINARY USER'S INSTRUCTIONS**

To set the time:

- Depress the button on the front marked "FAST" (1) for the advance of time, then depress the button marked "SLOW" (2) for slow advance until the desired time is reached.
- Ensure the time is set to the correct period as indicated by the AM/PM dot (3) indicator.

To set the alarm:

- Depress the button on the front marked "ALARM" along with the button "FAST" (1) or (2) "SLOW" to advance the clock to the desired alarm time. A dot (5) in the middle of the display will be light up indication the alarm is on.
- To switch off the alarm, depress the switch on the front marked "AL OFF" (6) once. Notice that the dot in the middle of display (5) will turn off indicating the alarm is off.

Snooze:

- When the alarm is sounding, touch the antenna once, the alarm will cease. after 9 minutes later, alarm will sound again. This gives the lazy sleeper another 9 minutes sleep. This 9 minutes delay may be repeated if you desire.

Radio Operation:

- Slide the switch to the right (7) to "MENU" position.
- Turn on and adjust the volume knob (8) to suitable sound level.
- Adjust the tuning knob (9) to a desired station.

Automatic clock radio operation:

- Slide the switch on right (7) to "AUTO" position, the radio will turn-on automatically when the alarm time is reached, and it will operate continuously for a period of one hour in the "AUTO" position.

Alarm Operations:

- Slide the switch (7) to "BEEP" position for producing a "BEEP" sound when the alarm time is reached.

NIGHT-LIGHT OPERATIONS:

- This is controlled by a slide switch on the left (10)
 - "ON" - light is on continuously.
 - "FLASH" - flashing at 1 Hz rate.
 - "OFF" - lamp is off permanently.

Rear Jacks:

- The following 2 jacks are located on the rear.
 - a) Connect the AC adapter to the left-hand side jack and connect to AC source. This provides all the power for Creature I
 - b) A standard earphone with 3.5 mm plug may also be connected to the right hand jack for private listening.

Wall-Mounting:

- Notice that the rear surface is provided with a wall hanging hole - so the Creature I may be wall mounted or table or desk mounted.

